

136 -174 MHz

## HORWIN FLP-150 Low-Pass filter

HORWIN FLP-150 - Low Pass Filter for attenuation of 2nd and 3rd harmonics in hybrid combiners.

The body material is extruded aluminum.

The connector type is specified when ordering.



FLP-150	
Frequency range, MHz	
pass band	<b>136 – 174</b>
stop band	<b>290-525</b>
Max. continuous power input, W	<b>150</b>
Insertion loss, db	<b>&lt; 0.3</b>
Reject attenuation, dB	<b>&gt; 40</b>
Nominal impedance, Ohm	<b>50</b>
SWR	<b>&lt; 1,3</b>
Connectors type	<b>N-male – N-female</b>
Temperature range, °C	<b>-30 ... +60</b>
Dimensions (H x W x D), mm	<b>26x40x100</b>
Weight, kg	<b>0,19</b>

